

> **E1S E**



Tipo Type	50 Hz - 3000 rpm - cosφ = 1						60 Hz - 3600 rpm - cosφ = 1					
	Pot. resa Rating Pot. salida	Rendimento% Efficiency % Rendimiento %		Pot. assorbita Driving power Pot. entrata		Pot. resa Rating Pot. salida	Rendimento% Efficiency % Rendimiento %		Pot. assorbita Driving power Pot. entrata			
		kVA	4/4	3/4	kW		HP	kVA	4/4	3/4	kW	HP
E1S10S G E	4.2	76.0	77.0	5.5	7.4	5	77.5	78.0	6.5	8.7		
E1S10M H E	5	77.0	78.0	6.5	8.7	6	79.0	79.5	7.6	10.2		
E1S10L I E	6	79.0	80.0	7.6	10.2	7.25	80.5	81.0	9.0	12.1		
E1S11M A E	8	79.5	80.5	10.0	13.4	9.75	80.0	81.0	12.2	16.4		
E1S11M B E	10	80.0	81.0	12.5	16.8	12	80.4	81.3	14.9	20.0		
E1S13S C E	13	82.0	82.5	15.8	21.2	15.6	82.4	82.9	18.9	25.3		
E1S13M D E	15	82.8	83.2	18.1	24.3	18	83.3	83.8	21.6	29.0		
E1S13M E E	18	83.0	83.5	21.7	29.0	21.5	83.6	84.0	25.7	34.5		